

► CLD-E | ELECTRICAL

CLD-E | AMP Draw, Circuits & Breaker Size Table

* With optional branch fusing for Single Point Power (SPP)

^ SPP by default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact Factory.

MODEL	AMP DRAW (Breaker Size)												
	208 / 1 / 60			240 / 1 / 60	208 / 3 / 60			240 / 3 / 60			480 / 3 / 60		
	Separate Supply Circuits		SPP*	Circuit 1	Separate Supply Circuits		SPP*	Separate Supply Circuits		SPP*	Separate Supply Circuits		SPP*
	1	2			1	2		1	2		1	2	
CLD-1-36E													
CLD-1-48E	25.4 (35)	24.0 (35)	49.4 (70)	43.1 (60)	29.2 (40)	-	^	25.5 (35)	-	^	12.7 (20)	-	^
CLD-1-60E													
CLD-2-72E													
CLD-2-84E	‡	-	‡	‡	30.6 (40)	27.8 (35)	58.4 (80)	26.9 (35)	24.1 (35)	51.0 (70)	25.6 (35)	-	^
CLD-2-96E													
CLD-3-108E													
CLD-3-120E	‡	-	‡	‡	45.8 (60)	41.6 (60)	87.4 (110)	40.3 (60)	36.1 (50)	76.4 (100)	38.2 (50)	-	^
CLD-3-132E													
CLD-4-144E	‡	-	‡	‡	‡	-	‡	‡	-	‡	26.9 (35)	24.1 (35)	51 (70)



Model CLD | Above Ceiling



Model CLD | Above Ceiling