

## ► EVE-E | ELECTRICAL

### EVE-E | AMP Draw, Circuits & Breaker Size Table

\* With optional branch fusing for Single Point Power (SPP) - REQUIRES A REMOTE ENCLOSURE

^ SPP By Default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact factory.

MODEL	AMP DRAW (Breaker Size)								
	208 / 1 / 60	240 / 1 / 60	208 / 3 / 60 Separate Supply Circuits			240 / 3 / 60 Separate Supply Circuits			480 / 3 / 60
	Circuit 1	Circuit 1	1	2	SPP*	1	2	SPP*	Circuit 1
EVE-1-30E									
EVE-1-36E	40.5 (60)	35.3 (45)	24.2 (35)	-	^	21.2 (30)	-	^	10.7 (15)
EVE-1-42E									
EVE-1-48E	‡	‡	46.4 (60)	-	^	40.5 (60)	-	^	20.3 (30)
EVE-1-60E									
EVE-2-72E	‡	‡	47.3 (60)	-	^	42.5 (60)	-	^	21.4 (30)
EVE-2-84E	‡	‡	26.2 (35)	44.4 (60)	70.6 (90)	23.2 (30)	38.5 (50)	61.7 (80)	31.1 (40)
EVE-2-96E									
EVE-2-108E	‡	‡	47.3 (60)	43.3 (60)	90.6 (125)	42.5 (60)	38.5 (50)	81.0 (110)	40.7 (60)
EVE-2-120E									



Elite Vestibule Exception Air Curtain | Entry